

# Computer Systems and -architecture

## Data Representation

1 Ba INF 2017-2018

Stephen Pauwels  
stephen.pauwels@uantwerpen.be

### Time Schedule

Exercises are made individually. Put all your files in a tgz archive, as explained on the course's website, and submit your solution to the exercises on Blackboard. **Write down all intermediate results on how you obtained the results.**

- Deadline: **November 12, 23u55**

### Exercises

1. Convert these positive numbers to base 10.

- (a)  $(101100011)_2$
- (b)  $(A36E)_{16}$
- (c)  $(111001010100)_2$
- (d)  $(641)_8$
- (e)  $(666)_9$

2. Convert to base 10.

- (a)  $(10110001)_2$  (2's complement)
- (b)  $(11)_2$  (2's complement)
- (c)  $(0.3112)_4$
- (d)  $(0.123)_{13}$

3. Convert to base 2.

- (a)  $(2017)_{10}$
- (b)  $(666)_8$
- (c)  $(14AD)_{16}$
- (d)  $(5.32)_{10}$
- (e)  $(42)_{16}$

4. Convert to base 2. Represent the negative numbers with 8 bits in *signed magnitude*, *one's complement*, *two's complement* and *excess 128*.

- (a)  $(-111)_{10}$

- (b)  $(-86)_{10}$   
 (c)  $(-131)_{10}$   
 (d)  $(-1A)_{16}$
5. For the following single-precision IEEE 754 bit patterns, show the numerical value as a base 2 significand with an exponent (e.g.  $+1.11 \cdot 2^5$ ).
- (a) 0 10010101 001110110000000000000000  
 (b) 1 01000001 101000000000000000000000  
 (c) 0 11111111 000000000000000000000000  
 (d) 0 00000000 000101110000000000000000  
 (e) 1 00010111 111001100000000000000000  
 (f) 0 10101011 011010000000000000000000  
 (g) 0 11111111 11010100010001010100010
6. Represent these numbers in the *IEEE-754 (single precision)* format.
- (a)  $(8982.5)_{10}$   
 (b)  $(2017)_{10}$   
 (c) NaN  
 (d)  $(-42.666)_{10}$   
 (e)  $+\infty$   
 (f)  $+0$   
 (g)  $(1.110101 * 2^{-134})_2$  (denormalized)  
 (h)  $(333.0)_{10}$
7. Suppose we are using a 15 bit floating point, in a normalized, base 8 floating point format, with a sign bit, followed by a 5-bit exponent with a certain bias, followed by three base 8 digits.
- (a) Determine the bias we have to use for the exponent, assuming we do not want to change the range of exponents we would have reached when using a 5-bit 2's complement exponent.  
 (b) Represent the number  $(-142)_{10}$  in our new format (with the bias from the previous question) as a binary string.  
 (c) What is the largest possible error that can be made using this representation?  
 (d) What is the smallest gap using this representation?
8. Write a Python program that, using the module `files`, does the following:
- (a) Read the given file `input.txt` using the correct encoding.  
 (b) Write the contents you just read back to file using the UTF-16 encoding scheme.  
 (c) Convert all characters to their appropriate code points.  
 (d) Convert the code points to their correct html code, make sure you can display a new line in a correct manner.

The module `files` has the following functions:

- `read_file(filename, encoding)`: this function takes a filename and reads it according to the given encoding and returns the resulting string.
- `write_file(filename, contents, encoding)`: this function writes the string `contents` to the file `filename` using the given encoding.
- `write_html_file(filename, contents)`: writes the string `contents` to a html file.

The module has the following encodings:

- ASCII
- UTF\_8
- UTF\_16